

**Subject:** No “clean bed” indicator with T-Max      **Number:** SRV0007

**Applicability:** SolarForce 648

**Date:** 12/27/04

**Symptoms:** “Clean bed” indicator fails to come on (..) on bed display and T-Max remote automatically indicates “unit ready” immediately after session even though parameter 9 is set to 1 (on).

**Explanation:** Faulty communication between SolarForce 648 and T-Max Manager Pro.

- Solution:**
1. Remove affected SolarForce 648(s) from T-Max remote “daisy chain”.
  2. Set address of bed to 255 (see below for specific instructions).
  3. Remove and reapply power to unit. Timer computer will restart with factory default settings.
  4. Set bed to appropriate address in salon chain.
  5. Connect bed back into remote “daisy chain”.
  6. Remove and reapply power to Manager, allowing Manager to find units in salon.
  7. Affected SolarForce 648(s) should now indicate “clean bed” after running a session.

***Setting the address in a SolarForce 648***

1. Make sure bed display is showing “0:00”.
2. Press and hold the STOP button for three seconds. Display will show the address.
3. Press the START button to count up to the desired address. Address will loop back to 0 after 255.
4. Press the STOP button to return to normal operating mode.

**NOTICE:** This document and the information disclosed herein are proprietary data of ETS, Inc. Neither this document nor the information contained herein shall be used, reproduced, or disclosed to others without the written authorization of ETS, Inc. except to the extent required for installation or maintenance of the recipient's equipment.

**CAUTION:** ETS, Inc. Service Bulletins are intended for use by experienced service technicians. They are written to inform those technicians of conditions that may occur in some equipment, or to provide information that could assist in the proper servicing of the equipment. If a condition is described, DO NOT assume that this service bulletin must be applied to your equipment, or that your equipment will develop that condition. Always consult your ETS, Inc. Technical Service Representative before performing any modifications to your equipment. When electrical service is needed, we recommend hiring a professional electrician.